

Restart jednotky HC2 pomoci LUA

```
--[[
%% properties

%% globals
--]]

function postMethod(data)
    local http = net.HTTPClient()

    http:request("http://127.0.0.1:11111/api/settings/reboot", {
        options = {
            method = 'POST',
            headers = {
                --headers here, using loopback (none required)
            },
            data = data.payload,
            timeout = data.timeout or 5000
        },
        success = data.success,
        error = function(err)
            print('[ERROR] ' .. err)
        end
    })
end

fibaro:debug("Probiha restart HC2...")
fibaro:sleep(3000)
postMethod("reboot")
```

ID článku: 187

Naposledy upraveny: 12 Feb, 2015

Revision: 2

Fibaro / Z-Wave -> Účinná stránka -> Restart jednotky HC2 pomoci LUA

<http://old-kb.yatun.cz/entry/187/>